

## Really Cool Touch Keyboard

The Really Cool Touch is a waterproof and contaminant resistant keyboard with an integrated three-button touchpad mouse. The touchpad is positioned on the right side of the keyboard under the same silicon rubber housing. This full size keyboard with tactile feedback keys plus mouse saves valuable desk space. The sealed and rigid surface is ideal for industrial, marine, and medical use, as well as other applications where moisture, cleaning, and durability are a consideration. Because the Really Cool Touch is also quieter than "standard" keyboards and mice, they are great for applications where noise generated from "key-clicks" and mouse button clicks are a problem.

### Installing Your Really Cool Touch Keyboard:

USB: Attach the keyboard cable to the USB port on your computer. (You do not have to turn off your computer. There is no software to install.)

### Descriptions of the Special Function Keys :



**Locking Key.** Press and hold this key for three seconds to lock the keyboard and the touchpad. Press and hold the key for three seconds to unlock the keyboard and the touchpad.



**Touchpad Locking key.** Press and hold this key for three seconds to lock the touchpad. Press and hold the key for three seconds to unlock the touchpad.



#### Cleaning Reminder Key.

To set cleaning reminder, press and hold the Left Ctrl key and press Cleaning Reminder key

- 1 time for every hour reminder,
- 2 times for every 2 hours reminder,
- 3 times for every 4 hours reminder,
- 4 times for every 8 hours reminder,
- 5 times for every 12 hours reminder,
- 6 times for every 24 hours reminder,
- 7 times for every 48 hours reminder, or
- 8 times for every 1 week reminder.

The **C LED light** (the LED to the left of the Num Lock LED) will blink when it is time to clean the keyboard. After the keyboard is cleaned, press the Cleaning Reminder key once to stop the blinking C LED and reset the timer to the last setting.



#### Backlight Key. (optional) Press this key

- 1 time for 30% brightness.
- 2 times for 60% brightness.
- 3 times for full brightness. (maximum current: 350mA)
- 4 times to turn the backlight off.

### Specifications:

#### Weight:

840 g (1.9 lb.)

#### Dimensions:

381 x 150 x 15 mm (15 x 5.9 x 0.6 ")

#### Cable length:

1.83 m (6')

#### Storage temperature:

-20 °C - 70 °C (-4 °F - 158 °F)

#### Operating temperature:

0 °C - 70 °C (32 °F - 158 °F)

#### Voltage and Current:

5 Volt, 26 mA without backlight.

#### Composition:

100% Silicone Rubber

PVC Cable

100% Latex free

#### System requirements:

USB interface

#### Number of keys:

109 = US Layout keys

#### Compliance:

FCC, CE, C-Tick, EN 60601 and IP68

#### Warranty period:

Limited lifetime warranty

### Cleaning Instructions:

1. To clean while the keyboard is plugged in, lock the keyboard by pressing the Locking Key for three seconds. (Locking Key description on the left).
2. Clean the surface of the product by wiping, brushing, spraying or dipping it. Use only rags, sponges or soft bristle brushes.  
**DO NOT place the USB connector into the fluid.**
3. Either wipe with dry cloth or allow to air dry.
4. Unlock the keyboard by pressing the Locking key for three seconds.

### Disinfectants recommended by Man & Machine, Inc.:

- **Chlorine based (max 10% solution)** - Chlorox, Novalsan, etc.
- **Formaldehyde based** - Formaldehyde Solution 37%, Vinco Formaldegen...
- **Glutaraldehyde based** - Aldacide 200, Lysofume, Wavicide, etc.
- **Phenol based** - Lysol I.C., Beaucoup, Magna Clean, Tek-Trol, etc.
- **Alcohol based** - Cavicide, Isopropyl Alcohol, Medicide, etc.
- **Oxidizing** - Hydrogen Peroxide 3% Solution, Lifeguard Series, etc.
- **Quaternary Ammonium** - Roccal-D, Bacto-Sep, Parvosol, etc.  
**Soap and water.**
- **DO NOT USE: Petroleum based cleaning fluids, such as Gasoline, Acetone, over 10% bleach solutions, temperature or pressure sterilization, buffing pads or scrubbing pads.**

You can email us at: [info@mmimd.com](mailto:info@mmimd.com)

or call us at: (301) 341-4900

In Europe, contact +31-23-5450185

[www.man-machine.com](http://www.man-machine.com)

MAN & MACHINE



CE IP 68

EN 60601

Assembled in the US.

THESE INSTRUCTIONS AND RECOMMENDATIONS HAVE BEEN PREPARED TO ADVISE THE PROPER METHODS FOR CLEANING YOUR PRODUCT. MAN & MACHINE, INC. OR THE LOCAL DISTRIBUTOR CANNOT ASSUME ANY RESPONSIBILITY FOR THE APPLICATION OF THEM. IF THERE ARE ANY QUESTIONS, PLEASE CONTACT PLACE OF PURCHASE OR MMI PRIOR TO CLEANING. SPECIFICATION SUBJECT TO CHANGE WITHOUT NOTICE.