

Really Cool LP Keyboard

The Really Cool LP is a waterproof and contaminant proof keyboard with low-profile keys. The sealed and rigid surface is ideal for industrial, marine, and medical use, as well as other applications where moisture, cleaning, and durability are a consideration. The low-profile keys have uncompromised tactile feedback and make cleaning between keys easy. And, because the Really Cool LP is also quieter than "standard" keyboards, they are great for applications where noise generated from "key-clicking" is a problem. This keyboard can also be equipped with our Backlight option where LED's are installed under each key for use in dark or low light conditions, and our "MAGFIX" option where magnets are installed in the base to help hold it in place on ferrous surfaces.

Weight:

702 g (1.8 lb.)

Dimensions:

381 mm x 140 mm x 15.3 mm
15" x 5.5" x 0.6"

Cable length:

1.83 m (6')

Storage temperature:

-20 °C - 70 °C
-4 °F - 158 °F

Operating temperature:

0 °C - 70 °C
32 °F - 158 °F

Voltage:

5 Volt

Current input:

26 mA - (w/o Backlight)
Up to max 300 mA (with Backlight)

Composition:

100% Silicone Rubber
PVC Cable
100% Latex free
100% RoHS Compliant

System requirements:

USB interface
(Not PS/2 Compatible)

Number of keys:

104 = US Layout with Windows™
plus additional function keys

Warranty period:

Limited lifetime warranty

*Specifications subject to change
without notice*

Installing Your Really Cool LP Keyboard


Attach the keyboard cable to a USB computer port.
(You do not have to turn off your computer. There is no software to install.)

You can email us at: info@mmimd.com
or call us at: (301) 341-4900
In Europe, contact +31-23-5450185
www.man-machine.com

MAN & MACHINE



For Keyboards with Backlight Option Function:

- Press the key on the top row with the  symbol to turn on, adjust, and turn off the backlighting feature.
- Pressing this key once turns on the backlight with 30% light intensity.
- A second time turns on the backlight with a 60% light intensity.
- A third time turns on the backlight at 100% intensity.
- A fourth time turns the backlight off.

Cleaning Instructions for Waterproof Keyboards and Mice:

- To clean the Really Cool LP Keyboard while it is plugged into the PC, press the left and right Control ("Ctrl") keys together for 3 seconds to lock the keyboard. After cleaning, press both keys again for 3 seconds to unlock keyboard.
- Clean the surface of the keyboard by wiping, brushing, spraying or dipping it. Use only rags, sponges or soft bristle brushes.
DO NOT place the USB connector into the fluid.
- Either wipe with dry cloth or allow to air dry.

Disinfectants recommended by Man & Machine, Inc.:

- **Chlorine based (max 10% solution)** - Chlorox, Novalsan, etc.
- **Formaldehyde based** - Formaldehyde Solution 37%, Vinco, Formaldegen, etc.
- **Glutaraldehyde based** - Aldacide 200, Lysofume, Wavicide, etc.
- **Phenol based** - Lysol I.C., Beaucoup, Magna Clean, Tek-Trol, etc.
- **Alcohol based** - Cavicide, Isopropyl Alcohol, Medicide, Dürr FD 322, FD 333 and FD 350, etc.
- **Oxidizing** - Hydrogen Peroxide 3% Solution, Lifeguard Series, etc.
- **Quaternary Ammonium** - Roccal-D, Bacto-Sep, Parvosol, Dürr FD 300 2%, Dürr FD 312 2%, etc.
- **Soap and water**

DO NOT USE:

Petroleum based products, such as Gasoline, Acetone, over 10% bleach solutions, temperature or pressure sterilization, buffing pads or scrubbing pads.

THESE INSTRUCTIONS AND RECOMMENDATIONS HAVE BEEN PREPARED TO ADVISE THE PROPER METHODS FOR CLEANING YOUR PRODUCT. MAN & MACHINE, INC. OR THE LOCAL DISTRIBUTOR CANNOT ASSUME ANY RESPONSIBILITY FOR THE APPLICATION OF THEM. IF THERE ARE ANY QUESTIONS, PLEASE CONTACT PLACE OF PURCHASE OR MMI PRIOR TO CLEANING.



Copyright Man & Machine, Inc. 2011